

Product data sheet

Characteristics

HOMT2020

MINIATURE CIRCUIT BREAKER 120/240V 20A



Product availability: Stock - Normally stocked in distribution facility



Main

| | |
|------------------------------|--|
| Product | Miniature circuit-breaker |
| Range | Homeline |
| Line Rated Current | 20 A |
| Certifications | UL listed |
| System Voltage | 120/240 V AC |
| Mounting Type | Plug-in |
| Number of Poles | 1P |
| Short Circuit Current Rating | 10 kA |
| Number of Spaces | 1 |
| Circuit Breaker Type | Tandem |
| Ratings | HACR rated |
| Electrical Connection | Box lugs |
| Wire Size | AWG 14...AWG 8 for 1 cable(s) (aluminium/copper) |
| Height | 3.13 in |
| Width | 1 in |
| Depth | 2.98 in |
| Tightening torque | 4 N.m for 2.5...6 mm ² (AWG 14...AWG 8) |

Environment

| | |
|---------------------------------------|----------------|
| Ambient air temperature for operation | 104 °F (40 °C) |
|---------------------------------------|----------------|

Ordering and shipping details

| | |
|-----------------------|------------------------------------|
| Category | 00046 - HOM/T 15-30A 1P; 15-60A 2P |
| Discount Schedule | DE3D |
| GTIN | 00785901065401 |
| Nbr. of units in pkg. | 10 |
| Package weight(Lbs) | 0.45000000000000001 |
| Returnability | Y |
| Country of origin | MX |

Offer Sustainability

| | |
|----------------------------------|---|
| Sustainable offer status | Green Premium product |
| RoHS (date code: YYWW) | Compliant - since 1323 - Schneider Electric declaration of conformity |
| REACH | Reference not containing SVHC above the threshold |
| Product environmental profile | Available |
| Product end of life instructions | Need no specific recycling operations |

Contractual warranty

| | |
|-----------------|----------|
| Warranty period | Lifetime |
|-----------------|----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.